



125VA and 250VA Inverters for Emergency Egress Lighting







Dual-Lite's LiteGear® compact central lighting inverters provide emergency AC power to existing indoor and outdoor lighting fixtures.

FEATURES

- True Sine Wave Output mitigates the effects of inrush current
- 1000 feet wiring distance between inverter and load
- Powers LED, Compact Fluorescent, Linear Fluorescent and Incandescent Lamp Types
- Operates normally on, normally off, or switched loads
- Surface Wall, Recessed Wall, and Recessed T-grid Ceiling mounting for the 125VA LiteGear®
- 90 minutes of emergency power for full load operation
- Self Testing/Self Diagnostics available with 250VA/220W version
- Adjustable Output version distributes dimmed output across larger loads ٠
- UL924 Compliant
- UL Plenum rating on Recessed T-grid Ceiling Model

Available with 125VA or 250VA capacity, Dual-Lite's LiteGear® compact central lighting inverters provide emergency AC power to existing indoor and outdoor lighting fixtures. The LiteGear® series is compatible with LED, incandescent, compact fluorescent and linear fluorescent lamped fixtures. As opposed to traditional battery packs, a LiteGear® inverter provides full light output for 90 minutes providing a brighter path of egress, and centralizes the maintenance of these fixtures to one convenient location.

Alternatively, the LiteGear adjustable output (-AO) versions, with two emergency circuits, work with 0-10V dimmer controls to eliminate the need for additional bypass devices or separate inverters for each switched load. Both circuits are userprogrammable to operate the connected fixtures at approximately 25%, 50%, 75% or 100% of nominal output during emergency mode.



LiteGe = (DUALUTE)



LG125S Surface Wall Mount or LG125R backing up outdoor steplights and wall packs; (6) 15W LED lamps

backing up outdoor bollards; (6) 31W LED lamps

FEATURES



AESTHETIC APPEAL

Allows use of existing AC Lighting

FULL LUMEN OUTPUT

Provides highest possible emergency illumination with fewer fixtures for code required 90 minutes

LOW MAINTENANCE

One centralized location and longer battery life than typical unit equipment

ZONE OF EGRESS

Provides emergency power for several fixtures in a defined area

OUTDOOR APPLICATIONS

Indoor storage protects emergency system from the elements for use with outdoor fixtures



THE COST-EFFECTIVE, EFFICIENT, CONVENIENT WAY TO PROVIDE EMERGENCY AC POWER TO INDOOR OR OUTDOOR FIXTURES

DC input switch isolates and protects batteries

Custom designed transformer for increased efficiency

DC battery fuse provides overload and short circuit protection

Durable tri-barrier terminal strips

Long-life, maintenance-free Sealed Lead Acid (SLA) batteries

LG125S Surface Wall Mount



Model Number	Input, Output Voltage	Enclosure Style	Total VA For 90 Minutes
LG125S/	120/120 or	Surface	125
LG125S-A0	277/277	Wall Mount	
LG125R /	120/120 or	Recessed	125
LG125R-A0	277/277	Wall Mount	
LG125T /	120/120 or	Recessed	125
LG125T-A0	277/277	Ceiling T-Grid	
LG250S /	120/120 or	Surface	250
LG250S-A0	277/277	Wall Mount	
LG250SI /	120/120 or	Surface Wall	250
LG250SI-A0	277/277	Mount	

PRODUCT SELECTOR



DIMENSIONS

LG125S WALL MOUNT SURFACE MODEL



LG250S AND LG250SI WALL MOUNT SURFACE MODELS



ORDERING GUIDE



Ordering Notes:

¹ Only available on 125VA/110W version.

² Only available on 250VA/220W version
³ Housing (93068300) and batteries (93068259) ship in separate cartons

⁴ Housing (93081978) and batteries (93068259) ship in separate cartons

Accessories (Order Separately)

RTSLP Remote Test Switch





ALERA LIGHTING

ARCHITECTURAL AREA LIGHTING

BEACON PRODUCTS

COLUMBIA LIGHTING

COMPASS

DUAL-LITE

HUBBELL CONTROL SOLUTIONS

HUBBELL INDUSTRIAL LIGHTING

HUBBELL OUTDOOR LIGHTING

KIM LIGHTING

KURT VERSEN

LITECONTROL

PRESCOLITE

WHITEWAY



701 Millennium Blvd. Greenville, SC 29607 Tel 864.678.1000 www.dual-lite.com

DL0603421 | 04/18

Copyright © 2016 Dual-lite, a division of Hubbell Lighting, Inc. All rights reserved. Please refer to online specifications for most up-to-date content as specifications are subject to change without notice.